

PANTHER



PN-TX-MD6M

| Transmitter PN-TX-MD6M | |
|------------------------|---|
| Article no. | PN-T13-6 |
| Frequency | 2,4 GHz , 16 channels |
| Code comb. | 4.000.000.000 |
| Output | 1 mW (by 50 ohm) |
| Buttons | 6 x 1 -step buttons |
| No. of batteries | 2 |
| Battery | Exchangeable |
| Type of batteries | LR03 1.5V AAA |
| Weight | ~ 128 g / ~ 0.3 lb |
| Dimensions | ~ 65 x 112 x 35 mm / ~ 2.6 x 4.4 x 1.4 in |
| Protection | IP65 |
| On/off switch | Yes |
| Bandwidth | 1.8 MHz |

The product picture above is for illustrative purposes only, actual product appearance might be slightly different.



PANTHER



| Receiver PN-RX-MN5 | |
|------------------------|--|
| Article no. | PN-R8-1 |
| Frequency | 2,4 GHz , 16 channels |
| No. of function relays | 5 |
| Duplex | No |
| Power supply | 12-24V DC |
| Dimensions | ~ 120 x 116 x 50 mm / ~ 4.7 x 4.6 x 2 in |
| Protection | IP66 |
| Bus system | None |
| Relay functionality | Momentary, Latching, Interlocking |
| Antenna | 1 internal |
| Temperature | -20 to +55 C / -4 to +130 F |
| Features/miscellaneous | Upgrade to 48-230VAC with "D12-2", analogue out with "D12-4" |

The product picture above is for illustrative purposes only, actual product appearance might be slightly different.